

Bluetooth PIR Beacon



CE declaration and ROHS2 compliance. Adhesive on the back for easy installation.



The Bluetooth signal start transmitting when the sensor detects movement.

Part no : SSD001

The device is a pyroelectric infrared sensor (PIR) and detects the infrared radiation by using the temperature-dependent feature. It suppresses the interference caused by temperature change, adopts the method of dual sensing elements complementary which improves the stability of the sensor.

This PIR sensor can be widely used in motion detection applications such as occupancy presence detection sensor.

Specification

Connectivity:	Bluetooth Low Energy 5.2
Bluetooth Indoor range:	Up to 50-90 meters.
Replaceable battery:	CR2450 with 620mAh.
Dimensions:	51x35x13mm.
Enclosure material:	PC/ABS.

Battery lifetime with 1s. advertising: 3 years.